

CAT C1.5 Generator Set
Serial No.: 1000028901<https://www.zeppelin.com/de-en/powersystems>

| | |
|-------------------------|-----------------------|
| Minimum Rating | 12.0 ekW |
| Maximum Rating | 13.2 ekW |
| Emissions/Fuel Strategy | R96/EUIIIa Equivalent |
| Voltage | 110 to 415 Volts |
| Frequency | 60 Hz |
| Speed | 1800 rpm |
| Duty Cycle | Standby, Prime |
| Engine Model | Cat® C1.5 |
| Bore | 84.0 mm |
| Stroke | 90.0 mm |
| Displacement | 1.5 l |
| Compression Ratio | 22.5:1 |
| Aspiration | Naturally Aspirated |
| Fuel System | Indirect Injection |
| Governor Type | Mechanical |
| Length - Maximum | 1400.0 mm |
| Width - Maximum | 90.0 mm |
| Height - Maximum | 1054.0 mm |
| Rated Speed | 1800 rpm |
| Maximum Rating | 13.2 kVA |
| Minimum Rating | 12.0 kVA |

This offer is without obligation. The offer is based on our General Terms and Conditions of Sale and Delivery. Changes to equipment and accessories required for technical reasons may be made at any time. Subject to errors, changes and intermediate sale. Statutory value-added tax shall be added to all price.

CAT C1.5 Generator Set
Serial No.: 1000028901

