

CAT C1.5 Generator Set

<https://www.zeppelin.com/de-en/powersystems>



Minimum Rating	12.0 ekW
Maximum Rating	13.2 ekW
Emissions/Fuel Strategy	R96/EUIIIa Equivalent
Voltage	110 to 415 Volts
Frequency	60 Hz
Speed	1800 rpm
Duty Cycle	Standby, Prime
Engine Model	Cat® C1.5
Bore	84 mm
Stroke	90 mm
Displacement	1,5 l
Compression Ratio	22.5:1
Aspiration	Naturally Aspirated
Fuel System	Indirect Injection
Governor Type	Mechanical
Length - Maximum	1.400 mm
Width - Maximum	90 mm
Height - Maximum	1.054 mm
Maximum Rating	13,2 kVA
Minimum Rating	12 kVA
Rated Speed	1800 rpm

This offer is without obligation. The offer is based on our General Terms and Conditions of Sale and Delivery. Changes to equipment and accessories required for technical reasons may be made at any time. Subject to errors, changes and intermediate sale. Statutory value-added tax shall be added to all price.

CAT C1.5 Generator Set

